

### LAMP REPLACEMENT:

- Switch off the electricity at the mains.
- Remove the guard & diffuser etc.
- Remove and replace lamp making sure that it is of the same type and wattage as stated on the label within the fitting or shown below.
- Replace diffuser and guard making sure that the gasket is intact and correctly positioned.

### REPLACEMENT LAMP TYPE:

Wattage: 40W  
Supply Voltage: 230 V.  
Size / Type: E27 GLS or suitable CFLi equivalent.

### EVENTUALLY, YOU MAY WANT TO REPLACE THIS LIGHT FITTING:

When your product comes to the end of its life or you choose to update or upgrade it by replacing it, please do not dispose of it with your normal household waste and please recycle where facilities exist. When you need to dispose of this fitting you can check with your retailer or local authority for suitable options. New regulations require the recycling of Waste from Electrical and Electronic Equipment (European "WEEE Directive" effective August 2005—UK WEEE Regulations effective 2nd January 2007). Environment Agency Registered Producer: WEE/GA0248QZ.



### IF YOU EXPERIENCE PROBLEMS:

If your product is defective or develops a fault, please return it to the place where you bought it. You can call our helpline for advice. The helpline will gladly give advice on any aspect of any Eterna Lighting product but may not be able to give specific instructions regarding individual installations.

**If in doubt, consult a qualified electrician.**



## SAFETY AND INSTALLATION INSTRUCTIONS



Model:  
**BH60BK**

#### Pack contents:


- 1 x bulkhead fitting
- 1 x fixing kit
- 2 x heat resistant sleeving
- 3 x grommets

### 60W Bulkhead With Wire Guard

These instructions are provided as a guideline to assist you.

**PLEASE READ THESE INSTRUCTIONS BEFORE USING YOUR NEW FITTING  
PLEASE RETAIN FOR FUTURE REFERENCE**

120119-SM



#### HELPLINE:

- T: 01933 673 144
- F: 01933 678 083
- E: [sales@eterna-lighting.co.uk](mailto:sales@eterna-lighting.co.uk)

Visit our website:

[www.eterna-lighting.co.uk](http://www.eterna-lighting.co.uk)

## General Information & Cleaning:

### READ THIS FIRST:

Check the pack and make sure you have all of the parts listed on the front of this booklet. If not, contact the outlet where you bought this product.

This product contains glass, care must be taken when assembling, fitting or handling to prevent personal injury or damage to the product.

**This product must be installed by a competent person in accordance with the current building and IEE wiring regulations.**

As the buyer, installer and/or user of this product it is your own responsibility to ensure that this fitting is fit for the purpose for which you have intended it. Eterna Lighting cannot accept any liability for loss, damage or premature failure resulting from inappropriate use.

**If in any doubt, consult a qualified electrician.**

Switch off the mains before commencing installation and remove the appropriate circuit fuse or lock off MCB.

This unit is suitable for indoor and outdoor use.

This product is designed for permanent connection to fixed wiring: this must be a suitable circuit (protected with the appropriate MCB or fuse).

This product is suitable for installation on surfaces with normal flammability e.g. wood, plasterboard and masonry. It is not suitable for use on highly flammable surfaces (e.g. polystyrene, textiles).

Before making fixing hole(s), check that there are no obstructions hidden beneath the mounting surface such as pipes or cables.

When choosing the location for your new fitting, give consideration to the ease and frequency of lamp changes. The fitting should not be installed in a position where it will be difficult to reach, especially if using incandescent lamps that typically have relatively short lamp life.

When making connections ensure that the terminals are tightened securely and that no strands of wire protrude. Check that the terminals are tightened onto the bared conductors and not onto any insulation.

This product is double insulated; do not connect either the blue/brown wires or any part to the earth terminal.

**IMPORTANT** - this fitting must be installed so that the lamp cap points downwards, i.e. the glass envelope is uppermost.

Always isolate at the mains before changing the lamp.

You are advised at every stage of your installation to double-check any electrical connections you have made. After you have completed your installation there are electrical tests that should be carried out, these tests are specified in the current IEE wiring and building regulations.

**If in doubt, consult a qualified electrician.**

### CLEANING:

Clean this product only with a soft dry cloth.

Disconnect the power and clean the exterior only of this fitting with a moist (not wet) cloth.

The diffuser may be removed and washed in a mild detergent solution. Ensure the diffuser is completely dry before replacing onto your fitting.

Do not use any chemical or abrasive cleaners.

## Installation:

### INSTALLATION:

Choose the location for your new light fitting according to the conditions listed opposite.

01. Undo the screw on the front of the fitting and remove the wire guard and glass diffuser.
02. Using the back of the fitting as a template, mark the position of the fixing holes.
03. Secure the fitting in position using the fixings supplied. If the fixings supplied are not appropriate to your installation, select suitable alternatives.
04. Make cable entry hole using an appropriate hole cutter and drill out fixing points in back of housing.
05. Pierce the rubber grommet(s) and thread the mains supply cable through. Note, do not make the holes in the grommets too large, they should be tight on the cable to ensure a good water-tight seal.
06. Thread the mains supply cable into the fitting and fit the heat resistant sleeving over the ends of the cable.
07. Make the mains terminations on the lampholder (L) live and (N) neutral.
08. Push the grommet(s) firmly into position in the cable entry(ies).
09. Fit a lamp, maximum GLS wattage available 40W or suitable CFLi equivalent.
10. Replace the glass diffuser and guard and secure in place using the screw provided.
11. Restore the power and switch on.